FTR CHECKLIST

- 1. Turn on PC and Monitor in courtroom
- 2. Make sure the mixer (black box) is working (red lights on box); flicker green when microphones are activated
- 3. Double-click FTR Reporter Icon to start program

Logon: ftruser Password: ftruser



- 4. Click the Start Recording button to begin recording; make sure record and archive lights are red; check mikes
- 5. Click Stop Recording button to stop recording click yes.
- 6. Play back mike test (switch to playback panel; open test for today's date; listen to make sure mike test recorded properly; stop playback

Moving and Controlling FTR

FTR is easily moved to any location on the screen by positioning the mouse pointer anywhere in the background area of the window, left-clicking and dragging it to the new location. The background area is any part of the window that is not a button, display area or slide bar.

The buttons at the top right of FTR control the way the program is displayed. Use these buttons to switch the program between normal and compact views and switch between the recording and playback panels, as well as minimize and close the program. Use the Properties option to establish default properties for the program. The table below outlines the function of each button at the top of FTR.

| Item | Description |
|----------------------|---|
| Panel Change | Toggles between the Recording and Playback Panels. |
| ₽ Compact View | Toggles between the Normal and Compact views. |
| ☐ Always On Top | Sets the program to always remain visible. |
| Properties | Displays the program properties. |
| | Displays the Help window. |
| Minimize | Reduces the size of the program window so that it only displays on the Windows taskbar. |
| X Close | Closes the program. |
| Panel Identification | Lists the name of the currently displayed FTR Reporter panel. |

Closing FTR


When recording and playback are finished for the day, exit FTR and shut down Windows prior to restarting the PC. If recording is in progress when attempting to exit the program, a message box displays indicating that the program cannot be exited until recording has stopped.

To Close FTR:

• Click the **Close** (**X**) button at the top of the FTR screen

Identifying The Recording Panel Screen Components

There are several screen components for using the Recording Panel as shown in the figure below. The table that follows describes the function of each element. Notice that the time is displayed in red.



Using Compact View (Recording Panel)

There is also a Compact View of the Recording Panel that displays a limited control set. This Compact View is designed to take up less screen space and will always remain visible (always on top) on the screen so that it is easier to work with other programs as recording occurs and still monitor the recording process.

To switch to Compact View:

• Click the **Compact View** button.



To switch to Normal View:

• Click the **Normal View** button



Using Compact View (Playback Panel)

As in the Recording Panel there is also a Compact View of the Playback Panel that displays a limited control set. This Compact View is designed to take up less screen space and will always remain visible on the screen (always on top) so that it is easier to work with other programs as recording occurs. Compact view in Playback Panel also shows blue numbers or dashes as in full view.

To switch to Compact View:

• Click the **Compact View** button



To switch to Normal View:

Click the **Normal View** button




The figure below illustrates the options available from the Compact View of the Playback Panel and the table that follows describes each option.





Listening To Recordings

After an audio file from the required date is loaded, it is ready to be played. There are several options available for controlling the playback of the recording as well as locating a specific time in the recording. The following figure illustrates the options and the table that follows describes each one.




| Option | Description |
|------------------------------|---|
| Rewind | Click this button to scroll backward in the recording at four times the normal playback speed. |
| Play | Click this button to play the currently loaded recordings. |
| Fast Forward | Click this button to scroll forward in the recording at four times the normal playback speed. |
| Current Play Time Display | Displays the current recording playback time. This display can be edited to locate a precise time in the recording. |
| Current Play Time Buttons | Click these adjustment buttons to adjust the position of the Current Play Time. |

| Option | Description |
|----------------------------------|--|
| Current Playback Time Display | Displays the time of recording being played back. |
| Channel Select Buttons | Turns channels on and off during playback. This allows the user to isolate audio channels while playing back recordings in order to focus on specific speakers. Click the required button to turn a channel off or on. |
| | See Appendix A for information on using keyboard shortcuts. |
| Normal View | Click this button to return to Normal View. |

FTR Recorder Quick Reference - Continued

Normal View




Normal View Keyboard Shortcuts

| Recording F | anel Keys | | |
|-------------|-----------------------|---|--|
| Key(s) | Description | | |
| Ctrl+F2 | Start recording | Start recording | |
| Ctrl+ F3 | Stop recording | Stop recording | |
| Ctrl+F12 | Start/Stop archiving | | |
| Ctrl+1 | *Channel 1 | If the channel is on then it stays on, | |
| Ctrl+2 | *Channel 2 | while all others are turned off. If the | |
| Ctrl+3 | *Channel 3 | channel is off it will be turned on, | |
| Ctrl+4 | *Channel 4 | while other channels are not affected. | |
| Ctrl+5 | *Turn all channels on | | |
| Ctrl+↑ | *Increase volume | | |
| Ctrl+↓ | *Decrease volume | | |

| Common Ke | ys (Also available from the Playback Panel) |
|------------|---|
| Key(s) | Description |
| Ctrl+Alt+V | *Switch Normal/Compact view |
| Ctrl+C | Change Panel |
| Crti+T | Always On Top |
| Alt+Enter | Properties |
| Alt+F4 | Exit Program |

Compact View



Compact View Keyboard Shortcuts

| Key(s) | Description | | |
|------------|-----------------------------|-----------------------------|--|
| Ctrl+↑or↓ | *Increase/Decrease volume | | |
| Ctrl+Alt+V | *Switch Normal/Compact view | | |
| Ctrl+1 | *Channel 1 | | |
| Ctri+2 | *Channel 2 | See the Normal | |
| Ctrl+3 | *Channel 3 | View Keyboard Shortcuts. | |
| Ctrl+4 | *Channel 4 | | |
| Ctrl+5 | *Turn all channels on | | |

FTR Playback - Quick Reference

To play FTR Gold audio:

- Click the Open Audio button to open the Open Audio dialog box.
- Select the required folder from the Folders/Drives list. Any FTR Gold audio will appear in the Location/Days list box.
- 3. Select the required location and day.
- 4. Click OK.
- 5. Click the Play button or depress the play switch on the foot control.
- Click the Stop button or release the play switch on the foot control to stop playing.

To control playback:

- Click the Fast Forward button to move rapidly forward or depress the fast forward switch on the foot control.
- Click the Rewind button to move rapidly back or depress the rewind switch on the foot control.

To control volume during playback:

- Drag the Playback Master Volume control tab up or down to adjust the overall volume.
- Drag the Playback Channel Volume control tabs up or down to adjust individual channels.

To turn channels on/off during playback:

- Click the required channel button to switch it off. This changes the channel button from green to red.
- Click the required channel button to switch it on. This changes the channel button from red to green.


To select an audio range:

- Open the required audio.
- 2. Position the Range Start Time control tab at the beginning of the required range.
- 3. Position the Range End Time control tab at the end of the required range.

To save an audio range:

- 1. Click the Save Audio button to display the Save Audio dialog box.
- Select the required drive and folder in the Folders/Drives list box.
- 3. Click Save.
- 4. When finished click Close.


FTR Playback - Quick Reference - Continued



Normal View Keyboard Shortcuts

| Key(s) | Description | | |
|------------------|--|--|--|
| F2 | Play | | |
| F3 | Stop | | |
| F4 | Rewind | | |
| F5 | Fast Forward | | |
| CTRL+ALT+S | Select stereo | playback | |
| CTRL+ALT+M | Select mono | Select mono playback | |
| Ctrl+T or ↓ | *Increase/Decrease volume | | |
| Shift+↑ or ↓ | Increase/Decrease speed | | |
| Ctrl+ ← or → | Move Range Start Time control tab left or right | | |
| Alt+ ← or → | Move Range End Time control tab left or right | | |
| Shift+ ← or → | Move Current Play Time control tab left or right | | |
| Ctrl+Alt+ ← or → | Move selected audio range left or right | | |
| Ctrl+F6 | Open Audio | | |
| Ctrl+S | Save Audio | | |
| Alt+1 | Select the Current Play Time Display | | |
| Alt+2 | Select the Range Start Time Display | | |
| Alt+3 | Select the Range End Time Display | | |
| Ctri+Alt+V | *Switch Normal/Compact view | | |
| Ctri+1 | *Channel 1 | If the channel is on then it stays on, | |
| Ctri+2 | *Channel 2 | while all others are turned off. If the channel is off it will be turned on, while other channels are not affected. | |
| Ctrl+3 | *Channel 3 | | |
| Ctrl+4 | *Channel 4 | | |
| Ctrl+5 | "Turns all che | mels on | |

Compact View



Compact View Keyboard Shortcuts

| Key(s) | Description | | |
|-------------|-----------------------------|-------------------------|--|
| Ctrl+↑ or ↓ | *increase/Decrease volume | | |
| Ctrl+Alt+V | *Switch Normal/Compact view | | |
| Ctrl+1 | *Channel 1 | See the | |
| Ctrl+2 | *Channel 2 | Normal View Keyboard | |
| Ctri+3 | *Channel 3 | | |
| Ctri+4 | *Channel 4 | Shortcuts. | |
| Ctrl+5 | *Turn all channels on | | |

FTR Log Notes - Quick Reference

Edit Mode

When creating log sheets for FTR Gold recordings it is recommended that you have your desired FTR Gold audio on screen before you start FTR Log Notes. In this way the selection of the location name is automated.

To create a new log sheet

- Click the New button.
- 2. Enter a Location or Description as required.

To add a log note

- 1. Select the last empty Speaker/Note field.
- Start typing or enter a glossary.
- A time stamp is automatically entered in the time field.

-or-

- Press CTRL+ENTER.
- 2. A new time stamp is entered immediately.
- The cursor is positioned in the speaker field waiting for input.

To create multiple lines in the same field

- 1. Enter the required text for the first line.
- Press SHIFT+ENTER.

To change glossaries

- Click the Properties button.
- 2. Select the Glossaries tab.
- Make the required changes by adding, deleting or editing entries. If necessary change the attached glossary.

Read-only Mode

To open a log sheet*

- Click the Open button.
- Enter Search Criteria for the required log sheets
- Click Browse to locate the log sheet storage folder.
- 4. Click Search Now.
- Select the log sheet you require from the results list and click Open.

To print a log sheet

- Click the Print button.
- Adjust printer properties as required.
- Click Print.

To set a range

- 1. Right click on a start log note.
- Click Set Range Start.
- Right click on an end log note.
- 4. Click Set Range End.

To save a copy of a log sheet

- Click the Copy As button.
- 2. Select a folder from the Save in box.
- 3. Type a name in the Filename box.
- Select a format from the Save as type box
- Click Save.

To link audio

- 1. Right click on a log note.
- Click Link to Audio.

To synchronize audio

- 1. Listen to your FTR Gold audio.
- Stop the audio when the content matches the first log note.
- 3. Right click on the first log note.
- Click Synchronize.

You can also copy, print and delete log sheets from the FTR Log Notes - Search dialog box.

FTR Log Notes - Quick Reference - Continued

